



Madras download R6

SangKyu Yu
S/W R&D Group – Europe
SAMSUNG electronics
2010. 02. 08

Before installing Infineon USB driver


- * We highly recommend the changing of USB Root Hub properties in Power Management
 - Uncheck** "Allow the computer to turn off this device to save power"



Driver Installation Guide[1]

Step1. Remove previous USB driver

- Run Remover.exe.



Driver Installation Guide[2]

Step2. Install Flash Loader utility USB Driver


- Unzip **FlashTool_E2_R6.zip**
- Run FlashTool_E2_R6\FlashUSB\Setup.exe.
- Press 'Exit' to complete the Installation of 'Flash Loader utility driver'




[Click install button]



[Click OK button]



[Click continue button]








[Click Exit button]


Driver Installation Guide[3]

Step3.



- Connecting target without battery and PC via USB cable
- PC executes the Hardware searching wizard automatically
- Please set the path as "FlashTool_E2_R6\FlashUSB"
- "USB flash loader utility" will be installed successfully.



Driver Installation Guide[4]




[Click continue button]




[Click finish button]

Flash Tool Usage Guide[1]

- Execute FlashTool_E2_R6\ FlashTool_E2.exe
- Check the version **v.4.41.3.35**



[FlashTool_E2_R6.zip]





[FlashTool_E2.exe]

**Flashtool version :
v.4.41.3.35**

Flash Tool Usage Guide[2]

a. Add binary files

Browser for file



*** These can be added via "Drag & Drop"**

Flash Tool Usage Guide[3]

* Download file list.

[Target Software]

- C3200XXXXX_bin.flc
- C3200XXXXX_cds.flc


[Resource File]

- C3200XXXXX.dffs

a. Binary sequence should be set as




a->b->c.

b. This can be done automatically by checking '**Customer Order**'



Flash Tool Usage Guide[4]


- a. Communication Driver should be set as **Infineon USB Driver**
- b. Choose the '**Erase whole flash before download**'
- c. Click [Start] Button.
- d. Click [Start USB1] Button.



Flash Tool Usage Guide[5]

a. Connect the power-off target with battery via USB cable

- The download will start automatically.



Thank You
