1: Установить драйвера и перезагрузить

компьн	
	¥
	msm7x27a ush driver
	PhoneUSBDriverSetup.exe

2: Распаковать архив в выбранную

папку.

名称	修改日期	类型	大小
📙 exe	2014/3/21 17:12	文件夹	
📙 InstDriver	2014/3/21 16:46	文件夹	
船 HTS_NET 写ESN MEID IMEI 号码知识介	2010/12/16 8:46	Microsoft Power	655 KB

3: Открыть папку

// 11	🐚 Diiwrap.uii	2011/0/20 20.43	应用/在广切 底	144 ND
"exe".	ErrMessage.dbt	2009/12/3 17:15	DBT 文件	5 KB
	Error	2011/1/6 16:21	文本文档	0 KB
	6 GSCLC	2012/10/19 13:38	配置设置	5 KB
	HTS_APP	2012/5/24 17:36	应用程序	1,296 KB
	B HISANY	2012/5/22 13:38	应用程序	1,309 KB
	HTSDBTplFile.mdb	2014/3/21 16:48	MDB 文件	1,316 KB
	🔒 HTSHELP	2008/5/5 11:25	编译的 HTML 帮	927 KB
	🔌 IFL.dll	2010/12/30 17: <mark>1</mark> 8	应用程序扩展	2,520 KB
	imfc42.dll	2010/12/8 16:16	应用程序扩展	997 KB
	msvcrt.dll	2010/12/8 16:16	应用程序扩展	316 KB
	PhaseCheck	2009/9/3 15:19	配置设置	1 KB
	PhoneCommand	2012/10/19 13:31	配置设置	1 KB
	AfTester	2012/10/19 14:58	配置设置	2 KB
	rscmu200 32.dll	2009/8/19 14:50	应用程序扩展	441 KB

4: Запустить приложение

S_Ann"								-		
МН	S_APP				-					
File	Operator	System	Setting	View Ru	n Other Test	Tools	Help			
	S 🖬 🔤 I		EF	SH						
Road										NUM
Ready	/									

6: выбрать имя пользователя "Admin" и нажать "ОК"



7: выбрать кнопку в меню наверху "Setting" - "Window

setting"	HTS_APP
•	File Operator System Setting View Pro Other Test Tools Help
	📾 🖬 📮 🗖 🔘 🖪 🗰 Window Setting
	Param Setting
	DateBase Setting
	To Set Window Num And COM.

8: выбрать "Other test" и нажать



9: в меню сверху выбрать "Other test" - "ESN/IMEI Write or



10: выбрать "WCDMA" - "Write" и нажать





Initial Setting Info IMEI Min: 000000000000 IMEI Mix: 99000000099999 Initial Set	Next To Write SF
Setting COM Port GSMI: [COM1 x] -> [WCDMA x]	Succeed Writed into
Phone Model: US8237(AJM-A18)	

11: Появится следующее окно.

12: теперь необходимо выбрать верный порт. В диспетчере устройств появится новое устройство – USB DIAG в разделе "порты COM и LPT"

(Remark: if the mobile has no IMEI inside, you will see the DIAG port directly from your computer.

if it has IMEI in mobile already, please remove battery for 5 seconds, then re-put battery into mobile. Continue Press "up volume key" without loose and insert USB cable with vour computer. vou will see DIAG port in computer.)



12: теперь необходимо выбрать верный порт. В диспетчере устройств появится новое устройство – USB DIAG в разделе "порты COM и LPT". Это СОМ порт выбираем в графе, на рисунке справа.

(Пояснение. Если на устройстве нет IMEI, то без дополнительных действий его нужно подключить к ПК через microUSB кабель. Если IMEI уже есть, нужно вытащить АКБ на 5 сек и вставить его обратно. Зажать кнопку громкости BBEPX и подключить смартфон кабелем к ПК. После этого появится устройство USB DIAG в диспетчере устройств)

計算机管理			ſ	US8237(AJM-A18) WCDMA 写双IMEI Write V12.0	
文件(F) 操作(A) 查看(V) 制	助(H)			Initial Setting Info	Next To Write
文件(5) 操作(A) 查信(V) 重 ★ ◆ ★ → <td< th=""><th>物(H)</th><th>操作 设备管理路 更多操作</th><th></th><th>Initial Setting Info IMEI Min: 000000000000000000000000000000000000</th><th>Next To Write SP IMEI: Err Succeed Writed Info IMEI:</th></td<>	物(H)	操作 设备管理路 更多操作		Initial Setting Info IMEI Min: 000000000000000000000000000000000000	Next To Write SP IMEI: Err Succeed Writed Info IMEI:
	Bluetooth 外間没新 Bluetooth 外間没新 Bluetooth 外間没新 Bluetooth 外間没新				Write
	Bluetooth 外围设备	-			EXIT

13: выбрать phone model A18+.

14: Ввести необходимые IMEI и нажать кнопку Write.

А18+ А18 їН»§ЙЁ	Ги РґЛ«IMEI Write V16.8	
Initial Setting	g Info	Next To Write SP
IMEI Min:	00000000000000000000000000000000000000	al Set IMEI: 111111111111
IMEI Max:	9900000099999	IME12: 88888888888899
MSN Min:	000000000000000000000000000000000000000	
MSN Max:	9000000000000009999999	Succeed Writed Info
Setting COM Port- GSM1: C Phone Mod	$DM14 \checkmark \rightarrow WCDMA$ $del: \boxed{A18+} \checkmark$	IMEI2:
		Write
		EXIT

15: После завершения процесса, появится зеленая надпись "ОК".

Теперь (US8237(AJM-A18) WCDMA 写双IMEI Write V12.0	
	Initial Setting Info	Next To Write SP
	IMEI Min: 000000000000000000000000000000000000	IMEI: 88888888888890 1
	IMEI Max: 9900000099999	
	Setting	IMEI: 8888888888888888
		OV
	Phone Model: US8237(AJM-A18) 💌	
	Write ESN IMEI OK!	
		Write
		EXIT